

S16-M

Socket for 8-pin Relays


Rated Load **10 A / 300 V**

Specifications

Rated impulse withstand voltage	3 kV rms / 1 min
- All terminals / DIN rail	3 kV rms / 1 min
- Terminal / Terminal	3 kV rms / 1 min
- Terminal / Coil	3 kV rms / 1 min
Cross-section of connecting wire	
- Single-wire	1 × 0.5 mm ² / AWG 20
- Multi-wire	1 × 2.5 mm ² / AWG 14 or 2 × 1.0 mm ² / AWG 18
Nominal screw torque	0.7 Nm
Screw Dimensions (mm)	M3 Pozzi 1 slot 2
Mounting	TS-35 or Back Panel Mounting
Ambient temperature	-40...60 °C / -40 ... 80 °C (no ice)
Weight	42 g



Connection diagram




Included Accessories

Retaining / Ejector clip, plastic CP-16

Optional Accessories (modules)

Free wheeling diode	RD16/DC12-240V
Green LED & free wheeling diode, 6-24V DC	RDL16/DC6-24V
Green LED & free wheeling diode, 24-60V DC	RDL16/DC24-60V
Green LED & free wheeling diode, 110-240V DC	RDL16/DC110-240V
Green LED, 6-24V AC/DC	RL16/UC6-24V
Green LED, 24-60V AC/DC	RL16/UC24-60V
Green LED, 110-240V AC/DC	RL16/UC110-240V
RC-Network 6-24V	RC16/UC6-24V
RC-Network 24-60V	RC16/UC24-60V
RC-Network 110-240V	RC16/UC110-240V

Dimensions (mm)



Technical approvals, conformities



Socket Selection for industrial Relays																									
Socket Type	Description	C2	C3	C4	C5	C7	C9	C10	C12	C16PTL / C18PTL	C18-A15PT	C21	C22	C31	C32	R7	R-Module	C52 / C53 / C64	C55 / C56	C83 / C85	CT2	CT3	CT32 / CT33 / CT36	CT515 / CT524	KDM
EC-11	Socket for industrial Relay		●											●	●										
S2-B	Socket for industrial Relay	●																				●			
S2-S *	Socket for industrial Relay	●										●	●									●			
S2-L *	Socket for industrial Relay	●																				●			
S2-P *	Socket for industrial Relay	●																				●			
S2-P0 *	Socket for industrial Relay	●																				●			
S3-B	Socket for industrial Relay		●											●	●			●	●				●		
S3-MP	Socket for industrial Relay		●											●	●			●	●				●		
S3-S	Socket for industrial Relay		●											●	●			●	●				●		
S3-P *	Socket for industrial Relay																	●	●				●		
S3-P0 *	Socket for industrial Relay																	●	●				●		
S3-M0	Socket for industrial Relay		●											●	●		●							●	●
S3-M1	Socket for industrial Relay		●											●	●			●	●				●		
S3-M	Socket for industrial Relay		●											●	●			●	●				●		
S4-J	Socket for industrial Relay			●																					
S4-L	Socket for industrial Relay			●																					
S4-P	Socket for industrial Relay			●																					
S5-M	Socket for industrial Relay				●													●						●	●
S5-L	Socket for industrial Relay				●																				
S5-P	Socket for industrial Relay																								
S7-C	Socket for industrial Relay					●											●	●			●				●
S7-I0	Socket for industrial Relay					●											●	●							
S7-16	Socket for industrial Relay					●											●	●							
S7-P *	Socket for industrial Relay					●											●								
S7-L *	Socket for industrial Relay					●											●								
S9-M	Socket for industrial Relay						●																		
S9-P	Socket for industrial Relay						●																		
S9-L *	Socket for industrial Relay						●																		
S9-P0	Socket for industrial Relay																								
S10	Socket for industrial Relay							●																	
S10-P	Socket for industrial Relay							●																	
S12	Socket for industrial Relay								●																
S12-P	Socket for industrial Relay								●																
S16-M	Socket for industrial Relay									●								●							
S18-M	Socket for industrial Relay										●							●							

* Discontinued, limited units may be still available from stock.

Socket Accessoires																	
Type	Description	S3-M	S3-M0	S3-M1	S2-B	S3-B	S5-M	S7-C	S10	S7-I0	S12	S9-M	S4-J	S7-L	S7-P	S9-L	S9-P
CA-11	Code Ring (BAG 5 PCS)					•											
C-A2	Neutral-Connector (BAG 5 PCS or 50 PCS)	•	•	•			•										
SC-3	A1-Connector (BAG 10 PCS)		•	•			•										
LH-1	Label carrier transparent (BAG 5 PCS)	•	•	•													
SL-36	Label holder transparent (BAG 5 PCS)				•	•											
SP-36	Labeling strips (BAG 5 PCS)				•	•											
L-16	Labeling strips (BAG 5 PCS)	•	•	•													
SD-1T	Lock lid transparent (BAG 5 PCS)	•	•	•			•										
SD-1W	Lock lid white (BAG 5 PCS)	•	•	•			•										
B20-G	Bridge Bar grey (BAG 5 PCS)										•						
B20-R	Bridge Bar red (BAG 5 PCS)										•						
B20-A	Bridge Bar blue (BAG 5 PCS)										•						
PS-W	Labeling strips							•									
S7-BB	Bridge bar (BAG 5 PCS (5 x 4))							•		•							
S9-CH	Labeling srib white (BAG 10 PCS)									•		•					
S10-BB	Bridge bar (BAG 20 PCS (5 x 4))								•								
S10-RH	Labeling srib white (BAG 10 PCS)								•		•						
S10-RT	Transparent Cover (BAG 20 PCS)								•								
SA-0	Wall Adapter							•	•		•						
SS-T	Transparent Cover							•									
SS-W	White Cover							•									
V10-G	Bridge Bar grey (BAG 5 PCS)										•						
V10-R	Bridge Bar red (BAG 5 PCS)										•						
V10-A	Bridge Bar blue (BAG 5 PCS)										•						
V40-G	Bridge Bar grey (BAG 5 PCS)										•						
V40-R	Bridge Bar red (BAG 5 PCS)										•						
V40-A	Bridge Bar blue (BAG 5 PCS)										•						

Retaining clip selection for socket and relay

Socket type	Made in	C2 ESP	C2 ESP + CT2	C2 ESP + CT2 Timecube	C2 IND	C2 IND + CT2	C3 ESP	C3 ESP + CT3	C3 ESP + CT3 Timecube	C3 IND	C3 ESP + CT3	C4 ESP	C4 CN	C5 ESP	C5 CN	C7 ESP	C7 CN	C9 ESP	C9 CN	C10 ESP	C10 CN	C10 IND	C12 ESP	C12 IND	C16PTL / C18PTL	C18-ATSPT	C21	C21 + CT2	C22	C22 + CT2	C31	C31 + CT3	C32	C32 + CT3	R3 ESP	R3 IND	R7 ESP	R7 CN															
EC-8	ESP	S3-C	HF-32	HF-32		HF-32		S3-C		S3-C	HF-32																																										
EC-11	ON																																																				
S2-B, S2-S	ON	S3-OM CP-15B S3-C	S3-CT	S3-OM HF-32	HF-33																																																
S20-B	ESP	S3-OM CP-15B S3-C	S3-CT	S3-OM HF-32	HF-33																																																
S2-L, S2-P, S2-PO	ESP	S3-C		HF-32																																																	
S3-B	ON			S3-OM CP-15B S3-C	S3-CT	S3-OM HF-32		S3-OM CP-15B S3-C		S3-OM CP-15B S3-C	HF-33																																										
S30-B	ESP			S3-OM CP-15B S3-C	S3-CT	S3-OM HF-32		S3-OM CP-15B S3-C		S3-OM CP-15B S3-C	HF-33																																										
S3-MP	ESP			S3-OM CP-15B S3-C	S3-CT	S3-OM HF-32		S3-OM CP-15B S3-C		S3-OM CP-15B S3-C	HF-33																																										
S3-S	ON			S3-OM CP-15B S3-C	S3-CT	S3-OM HF-32		S3-OM CP-15B S3-C		S3-OM CP-15B S3-C	HF-33																																										
S3-L, S3-P, S3-PO	ESP			S3-C		HF-32		S3-C		S3-C	HF-32																																										
S3-M0	ESP			S3-C	S3-CT	HF-32		S3-C		S3-C	HF-32																																										
S4-J	ON			S3-OM CP-15B S3-C				S3-OM CP-15B S3-C		S3-OM CP-15B S3-C	HF-32																																										
S4-L, S4-P, S4-PO	ESP			S4-CL				S4-CL		S4-CL																																											
S5-S	ESP																																																				
S5-M	ON																																																				
S7-C	ON																																																				
S7-H0	ESP																																																				
S7-H0	ON																																																				
S7-16	ESP																																																				
S7-P																																																					
S7-L, S7-PO	ESP																																																				
S9-M	ON																																																				
S9-P																																																					
S9-L, S9-PO	ESP																																																				
S10	ON																																																				
S10-P	ON																																																				
S12	ON																																																				
S12-P	ESP																																																				
S16-M	ON																																																				
S18-M	ON																																																				